Chapter 3

GPS and Its Application

GPS, Global Positioning System, is an advanced technique well developed and widely applied in recent years. By receiving the signals from the GPS satellite, it is easy to get the three-dimensional position information for any point on the earth. Because of its ability of all-weather, global, three-dimensional positioning, the coordinate system used should not be a local coordinates of any country or region, but a global coordinates. At present, the coordinates used by GPS is WGS-84, which is a global uniform geographic coordinates. WGS-84 belongs to protocol coordinate system and its origin located at centroid of the earth is also perfectly defined.

An important problem in GPS measurement application is to determine the difference of benchmark of geographic measurement between local coordinate system (for example, China 1954 Beijing coordinate system and 1980 national coordinate system) and global coordinate system and take transformation between them. In order to get highly precise absolute position and navigation, we have developed a GPS coordinate transformation software with Visual C to process the data rapidly. Because of the difference among the independent coordinate system in different country, the error among the coordinate systems should be seriously treated during the application of GPS data. In other word, if higher precision is required, the coordinate transformation is necessary.

In order to apply GPS in precise detection and controlling forest damage, we have developed the GPS coordinate transformation software and flight line design software, and so on.

1. GPS coordinate transformation system software

This software has a friendly user interface and can be directly installed on the computer with Windows 95, Windows 98, and so on. The following figure is a illustration of the interface.



In terms of the difference in the data transformation mode, this software can be divided into two parts: single point mode and file mode, and their functions also vary respectively.

1.1 Main function of single point transformation mode

1.1.1 Calculation of transformation parameters

This software sets the lower precision coordinate and elevation transformation parameters that are suitable for country range as default parameters inside. At the same time, it provides users the interface to calculate local coordinate

and elevation transformation parameters. Users take coordinate and elevation transformation in local region with data existed to get a special transformation parameter as local value that will be used in high precision transformation

Antris呈採精換系统 [Stiff courd V2.0] 文件(P1 转换方式(T) 高原設影(6) 出版特别(C)	· 後景(5) 祝留(7) 帮助(8)	
South in the second of the second second		
ilitical Alter		
Berrichten Fill Faster-4 at off		. I I I
又律(L) 转换万式[1] 资料投款[4] 坐标转换(L)	金墨(2) 加魯(2) 老弟(3)	- 10 A
🕅 🖧 🕀 🍪 🕄 🗸 🗱	11 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	
UPSCOON 24 UPSCOON 24		2.4 EPSONON 2.4 EPSONON 2.4
CPS:coold 2.4 CPS:coold 2.4		2.4 GPS:00010 2.4 GPS:000

1.1.2 Choice of transformation mode

According to the magnitude of data, users can choose different data organization mode.

ag (FSa) 标种教系统 ExpScourd, V2.03	
文件(I) 教校方式(I) 高斯拱影(g) 坐标教教(I) 设置(g) 视窗(V) 帮助(M)	
THERE	

1.1.3 Gauss projection's positive and negative calculation and zonal change calculation

The topographical map series in each country adopt UTM or Gauss projection mode. Because topographical maps are often basic map for management in forest production, the problems of positive and negative calculation to coordinate often occur.

Concession and for	Sceard V2.01		A Description of the Second	
从件位】特殊办大位)	会局設計(15) 主切特点(1) 当時時代ご知(2)	でま14日 Cur14日	ALBECS ANALOS	
• • • • • •	端前目出版(反前(2) 南南目出版(約(第))年(1)	Curl+L Curl+Y	18	
	NOVIDE 01 11 11 11	C17473		

1.2.10	44	44	لام	120
escound 2.4	へ込 たちに ²⁰¹¹ 第入经纬度 日 日 日 日 日 日 日 日 日 日 日 日 日	[N] 〒九	本 9箱出 0番号 0600公里	und 2.0 GPSC
Second 2.4	单位: 度: 255 ^{20,010} 安新带 5.5度带	lt o	系 凉 14系 按 10系 GP5 ²⁰	10114 2.11 G2550
Scound 24	 3度帯 任意常 	200	-	and 24 Class

12.0	A	~~ ^>	124	
precional 2.4 UPS	LEUGING 第 輸入生标值 次 回	Y坐标値 □ ☆常号 □ 戸 含500公里	UPSound 24	5125c
appictured 2.4 GPS	All and All	坐标系 ~ 北京 54 系 ~ 西安 60 系	SIPErcound 2.0	51250
Parand 24 Sta	○3度带		GPScound 2.4	


Because the UTM and Gauss-Kruger projection adopt zonal projection mode and has distinction between 3 degree zone and 6 degree zone, users will encounter the problem about the right angle coordinate system when they use the different scale topographical map or make operation at the edge of different zone. For the facility of analysis, it is necessary to make the zonal transformation calculation to uniform the coordinate system.


A	- A	λ		۱.	a P
3、 3005分量及有计划 第一带 输入坐标值		¥坐标输入 ☞ 含带号	第二帝 投影帝 ぐ 6 度帝	Y坐标输出 反 加带导	
X1:0 V1:0 投影響	[m]	P 含500公里	 ご 2 度帯 ご 3 度帯 ご 4 景帯 	₽ 加500公里	2
u ^v 投影幣	419/1-33 6 年号 6 経業		袖子午线 「 帯号 6 経度	75 💽	đ

1.1.4 Cross transformation among WGS-84, Beijing 1954 and Xi'an1980 coordinate system

Because the topographical map surveyed at different time adopt different coordinate, users often confront the problem of transformation and joining. We must resolve the problem that exits in the high precise cross coordinate transformation of geographic coordinates, Gauss-Kruger coordinates, spatial right angle coordinates among different systems.


	1000 6 7 19 12		THE BOARD	-1 MININ	APRILE 2 MINUT	WWI(C) WWI(C) RECOVERNMENT County HEALTH County RECEIPTION (C)	ال ة قرر .
president 24	、3.2. ⁹ (特殊方式	.3 ²⁹ 第八主标值	.12	い 次期/年	2 ²⁰	325000	
19500011 2.11	WGS ##茶→ 54茶 ■ 输入坐标格式 ■ r 大地坐标 度分秒 ■	8: 0 1: 0 1: 0	(N) (E) (m)	< 6 度帯 < 3 度帯 < 任志帯	2.10		
	输出坐标格式	Y坐标稿出 反加带号 反加定的公司	(**** (*** (***	5		125 eur	
Scoon 2.0	◎ 高斯坐标 正常高 ■	補定[0]	取油口	#Rign	2.10		





1.1.5 Setting transformation parameters

Users can set the coordinate and elevation transformation parameters (for example, provided by the third attendee) as default value or local value.



1.1.6 Setting data file table

For the facility of understanding and output, users can make diverse setting for the data table.

PScoond 2.0	. and 2.4	ard 2.4	10 2.W	1011 2.W
apset.	設置影響生件素描 列标题	读入数据文件	保存数据文件	E CLPS
	字体类型: 中文 ≥ 前景颜色: ● 设置図	으 含列杯题 뎐 含序号	P 含列标题 P 含序号	
125/20074 2.4	文本 輸入颜色:	输入/输出小数 大地经纬度值: 坐标、高程值: [3	12/12	ord 2.4 UPS

1.1.7 Windows and Help

Convenient tool buttons and illustration for help.

antaleses was a latter w	
文件(2) 特殊方式(1) 密斯投影(全) 坐标转换(2) 设置(2) 情密(2) 移動(3)	
R #ASH - 200 0 2 4 13 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	
* MOR(2)	

(COSEC) 特殊方式([) 副 文件(g) 特殊方式([) 副	46612.0) 415日(2) 金银粉路(2) 初量(2) 1318	IN I	entrona	× Dia
		2 4	2011年2月11日1 10月1日月1日(11)	
	. 0		关于 *crs生乐教换系统* (b)	

1.2 Main function of file conversion mode

in certain with the Doctory	a vz. cil	
文件(四) 防操方式(2) 務新部	(教授) 坐保神教(に) 後者(に) 明慶(2) 秋期(10)	
R #Attais		

1.2.1 Gauss-Kruger projection's positive and negative calculation

20172単版神樂単版 [GTSuerd V2.0] - Writhell Ma 文件(E) 瞬時(E) 特殊方式(E) 特許点面(E) 後置(E)	
Thurleff Mr	
特教类型·高斯投影正算 • 5331 • 5	
学校 <u>AS</u> 54大法/5度8 54大法経済1 	54高新业积2 54高新业积2

ale ceres 化林林氏法 Diversion of 12,000 — Texts (Look) and	
文件(2) 機構(2) 特殊方式(2) 特殊死型(2) 设置(2) 说習(2) 留中(3) 税物(3)	
9 9 9 9 9 9 9 9 9 9 9 9 1 1 1 1 9 1 1 1 9 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	
Contra Carela angle in the contra carela and c	
转换类型: 高斯投影反算 Ⅰ 5 度带 Ⅰ 54系 Ⅰ	
#\$ AS GALLER GALLER GALLER GALLER	
1	

1.2.2 Gauss-Kruger projection's zonal change calculation

(22115)1103月611(22000-0-12-03) - Tota (1645-196 1412) - 146512) 和美巧式(121-新美術和(121-波波(12)-波波(121-181-04) - 発表の)	
980 s 3 3 320 V	
Uots (2+43) spa	
转换类型: 高斯投影换带计算 54系 三	
井平 三名 SAASSARD SAASSARD (1981年1) 日本日本 7-1	P482 S1高新至保護 S4高新主保護

1.2.3 Cross transformation among the three coordinate systems

(2011年1月1日)	※ EG7500 or 8 V2.0月 - Ua 钟格方式(1) 钟格特型			##100		
010010	1) 🐼 🖄 📰 💷	s a y -	Is mind		28	
Untitledt vet						
转袭英型:	₩GS-84第→54系	• 大地坐住	承→商新生村	· · · · · · · · · · · · · · · · · · ·	サラ 大地高	•
#4	WGS-84系→54系 154系→WGS-84系	4大的感激1	ostinais	-	542064462 I	54.50
11.0	WGS-84系→90系					

(#1主接接単語集合#Second W. 00 - C. Wy Decementalisest veb (#12) 編載[12] (秋東大王)(1) 秋季本朝(2) 保留[13] (秋朝(2) 第二11) 秋朝(14)	
NAN & R R FF & G FFIT FOR S	
转换关型: 54系→WGS44系 高斯坐标→大地坐标 「6 度带 大地高	n l

2013年2月初始第三統 [15:00ml Y2:0] - 7613164 55 文件(2) 続任(2) 特美方大(2) 特美英型(2) 現世(2) 現世(2) 報助(2)	
N 2088 - DR X - C & R A & R 7 2 ? ¥?	
大地坐标→高斯坐标	日本時を続き 「「「大学術で
1 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	

(注意のなどを計算)手術 次かり21 の第二(注)	[GFSceard V2.0] - Yoti (1+64 +45 利徳方式(1) 初後祭業(2) 改革(2) 後期(2	1 1010111 3010-1111
A DATA DATA DATA DATA DATA DATA DATA DA	1 🐼 🖄 🖬 🗉 🖉 🖬 🖉 📑	
10 000 12 005 +15		
转换类型:	WG8-84系→54系 • 大地坐标-	→高斯坐标 🖃 🛛 6 度带 💌 大地高 🖃
		04天法典# 54支持 3 5 开 5所生物* 545

20日本主任教教系统 [015acord V2 0] - Unit(1add set 文件(2) 编辑(2) 特殊方式(2) 特殊并以(2) 设置(2) 说句(2) 第(1(2) 册助(2)	
	real
• 转换类型: ₩GS-04系 • 54系 • 大地坐标 • 高斯坐标 • 6 度	带 三 大地高 三
102 32 artisting artisting artisting artisting	CA201 - 1 2 A A-++63

200	7 KR -		(c) 祝春(c) 节 [111] [11] [11] [11]	eria Esta eria	
<u>=0103</u>	(C) 🚳	M	# 🔊 🛛		
Untitled5.	±58				E C

a @S生标特换系统 S@Facord N2.03 - Watitle @.blb	
2件(2) 銅像(2) 特殊方式(2) 特殊高量(2) 後載(2) 視園(2) 欄口(2) 帮助(3)	
1 2000 A 41 5 182 2 101 1 1000 2	
🔁 Oni (1+08 blh	
转换类型:大地坐标→直角坐标 🖃 💶 54系	
大地坐标→真角坐标 序号 自角坐标→大地坐标 大地经夜L 54大地高H 54直角曲板I 54直角曲板I	5420

ars性标转换系统 ()	25occr4 12.0] - th	titledT.blb	Sector Association	Concernance -		
太付(2) 网络(2) 躬	與方式(1) 对换类型	(1) 初世(2) 現象(X) 1800 (X)	#18,(23		
1 文件特許		ne ga i	1 1	9 4?		
💭 🚳 📭	61 🖽 🔚 🔟	e e 🖉 📑	I stolate		3 8	
This theft, 12b						리미즈
转换类型: 天式	也坐标・直角坐椅	· 54乐 54系	-			
#4 AS	SACTHERED	54 th 80 %	D.200 H	54 21.00 2658	148.8461	542.94
1		WGS-84 *				

1.2.4 Conversion NMEA-0183 real-time outputting data to 54 or 80 system

The main aim is to realize the integrity of GPS and GIS through converting the 0183 data provided by GPS receiver to plane right-angle coordinate system matching with topographical map data.

125courd 2.0	124		. s 2.0	10 2.N
125:00	MS-04系与54系/80系相互转换 转换方式	输入坐标值	投影带	10 - UPS
	WGS-84茶-+ 54茶	· 8:	M	
. 2.4	输入坐标格式	L: 0 H: 0	日 ~3度 利 ~任報	(市)市 (小))
PScourd 2.0	 ・ た地座标 度介秒 ・ 直角坐标 	 Y坐标输出 	的不会法	5175
	输出坐标格式	—————————————————————————————————————	r	

1.2.5 Calculation of GPS waypoint is the basic data for GPS navigation.

X4年 (※ 一番98.8527年 (2) と18.8521年1年) 「サ19.852月2日 - 042.852/11日から、「-4.852 FCG 第1日 - 042.852/11日から、「-4.852 FCG 第1日 - 042.552 FCG #			
All March (Start and Start) (· · · · · · · · · · · · · · · · · · ·	CATHERS GALLACE FORS 3	
#38.5 xtht名 [が始え [xtr 三 路径 C Wy Discussion			
#38.5 xtht名 [が始え [xtr 三 路径 C Wy Discussion			
諸任 C Wy Decuents	NGC. INCOMPANY AND	2008年- [F.St _]	GAPE-Income man -
諸任 C Wy Decuents	1	and a state of the state	
filt ()		THE C Wy DICUMARKS	
			1000 P 20 1
INT LATIFUR LOUTINE JATE THE ALT RESCRETTION	SUTTING SUTTING	JATE TINE	ALT RESCRIPTION
#5100 6667 E11900 6167 02-7AP-97 14 25 47 306 72	1 E3100 0067 E11900 6167	02-TAE-97 14 25 47	306.72
80300 1600 EL1828 2500 02-JAF-27 14 25 47 406.72	Z #3300.1435 \$11828.2500	02-JAS-27 14 25 47	408.72
80301.0667 111928 2667 02-JAF-97 14-25 47 406.72		02-JAE-97 14:25:47	406.72
#XXX1 7450 \$11000 4800 02-5AF-37 14 28 47 108.72		02-348-07 14 28 47	
#3102 6333 T11900 6667 02-TAF-97 14 25 47 306 72			
		02-TAE-97 14.25.47	306.72
#3303.5000 #11025.4033 02-748-97 14 25 47 406 72	5 #3102 0335 EL1900 6667		
		02-348-07 14 28 47	
		02-TAX-27 14 25 47	
	5 #3102 0335 EL1900 6667		

1.2.6 Calculation of flight line file with waypoint


To compile flight line (or route) file with selected waypoint data.

ERE/*8	fest	*#& DTT	- 146	C:Wy locus	ate	1	
n 11000	LATETRE	LOBORTUDE	JAIL	TINE	ALI	DESCRIPTION	BICTH
	LATITION K100, 5667 10100, 1003	10841700E 211300 5347 211300 5349	MIX 02-348-37 02-348-37	1188 14 25 47 14 28 47		MULTIPIOS	500 400 500 300 300

1.2.7 Calculation of route file with flight line type

Forest flight task usually chooses its flight mode according to the topographic condition, such as double direction flight, single direction flight, interval flight, and so on. So different flight line sequence will come into being in the same task region with different flight type.

55 4.4 autoballity autoballit	IX.
###27 (CHEANAR) #0940 (2010-000) #113 DEM (DARSE (1999-000) 日) (2010)	
450-0 00-0 00-0 0 0000 0 0000 0 0000	
	Sugar 1
T SAE IT LOW BALANCE .	531 H-1
C 10.6 C 10.97	
THE D CARE BO C. Gran Davidoure	222 I I I I I I I I I I I I I I I I I I
NAME	100 million (1990)
PO JE WEIGHT & WEIGHT WEIGT	1000 C
No. 2 Contraction of the inclusion of the loss of the	
	and the second se
The A (
E Internet internet internet	
THE LATTING LOWTING MIL THE ALT HOUSE	
That Blief 1211 Bliefs that OF-THEOR SECTION OF	
NUMBER 1045 BLOOM FYON ON-JUN-ON 12 21 28 200 84	100



1.3 Upload of flight line and download of flight track

In forest production department, most users use the GPS receiver of GARMIN Company as navigation tool. Our receiver is GARMIN GPS 195, and the flight waypoint or flight route file can be directly converted to the data format (*.RTE) recognized by GARMIN receiver.

	- CARSINGIA	E CERTERIA E
司規制		
目機関		
	IIIII I	

Fig. 3.1 Route, waypoints and preparatory waypoint

ile Name: [1 Arectory: c	sturte SK30/CK52		
www.	Directories:	Files:	
ind as ind ba ind c: ind c: in	•	• samplearte lest.nte	
		•	•

At the same time, we can upload the data (for example, flight track data) from the receiver for analysis.




Fig. 3.2 Comparison of route and track

2. Differential GPS positioning

Since May 1st 2000, the United State has abrogated the SA policy, which promotes the precision of GPS realtime positioning from 100m to 15m or so, but for more precise positioning and navigation task (for example, air spraying), DGPS technology that is better must be adopted to improve the positioning precision to meter level or sub-meter level.

DGPS is a technology with base station at known point, amendatory value of observation were measured and conveyed to the mobile station through digital radio system. Mobile station observes the satellite pseudo-distance code that can be used for positioning calculation after differential amendment.

To well understand the GPS and the technology related with GPS and rapidly apply them in practice of the flight detection, preventing and controlling of forest diseases and insects, we used three suits of real-time dynamic differential GPS system whose basic components are displayed as follow:

Base station	NovAtel 3151R
Mobile station	Garmin 195 (Navigation), TRIMBLE AgGPS 132 (Positioning)
Digital radio station	TM32
Amplifier	RFA96£-35W
Antenna	full direction 15DB (used in base station)
	Knife antenna (used in mobile station onboard aeroplane)
	Scourge antenna (used inside forest)
GPS antenna	Mp surveying antenna (ST430 in base station, ST410 in mobile station)




Fig. 3.3 The structure of the base station




Fig. 3.4 The structure of the mobile station

GARMIN GPS 195 is a 12 channel navigation product, which obviously can satisfy our request of highly dynamic real-time navigation, and also mainly is used in navigation in practice. TRIMBLE AgGPS 132 receivers are combined with high-performance GPS reception with radiobeacon DGPS capability. Additionally, AgGPS 132 receiver contains The ChoiceTM technology, enabling OmniSTAR and Racal LandStar real-time differential capabilities. Users can get submeter positioning precision, so it is a good choice for high precision positioning.

For insuring the data quality and lowering error rate, high frequency communication equipment (frequency is 450-470Mhz) is adopted. Because its signal can be transmitted directly, it is especially suitable for air real-time navigation. The baud rate of data transmission is usually 9,600.



Fig. 3.5 DGPS and its application

3. Flight quality assessment

After the ground static, ground vehicle mobile, air flight mobile test of DGPS' software and hardware installed, we participated the practice of the flight monitoring, preventing and controlling of forest diseases and insects in many provinces in China, such as Anhui Province, Guangdong Province, Guangxi Zhuang Autonomous Region. Our tasks mainly lie in applying the DGPS technology in flight navigation to completely replace the traditional practice mode of manual navigation that costs so much manpower and material resources, and take flight evaluation to assure the quality of detection, prevention and controlling in terms of the recorded flight track data. Two figures beneath are two tracks in a practice of prevention and controlling, one is without GPS navigation(Fig.3.6), the other is with GPS navigation. The flying quality greatly improves(Fig.3.7). Combined with GIS, we can get the precise position and range of regions that are omitted or repeated during spraying(Fig.3.8).




Fig. 3.6 Plane track in protection without GPS navigation




Fig. 3.7 Plane track in protection with GPS navigation (purple-designed flight line, red-flight track)




Fig. 3.8 Integration of GPS and GIS in flight assessment

4. Applications of DGPS in management of forest insects and diseases

Through whatever detection method, airborne or satellite remote sensing, we can get different scale hazard point or region. As for forest protection managers, sufficient information of disease and insects is important to choose correct prevention and controlling measure. How to rapidly and precisely determine the correct location where hazard happens and correctly analyze the cause is crucial to lowering loss of forest damage. GPS's function of navigation and positioning provides possibility and technological assurance for the rapid positioning of the calamity location.

4.1 Navigating in air prevention

To prevent forest insects and diseases by plane is a widely used technique and it is usually navigated by ground people or by the experience of the pilot. The backward navigating method has caused that some areas are not sprayed while some other areas are double sprayed. This has greatly impeded the efficiency of prevention. Since the 1990s, the technique of GPS has been widely used in various fields, and it provides a possibility to improve the navigating system of the aerial prevention system.

Since 1998, DGPS has been introduced into the aerial prevention system in China, the efficiency has been heightened and the cost has been reduced. The most important is that high spurting accuracy is achieved so that measures can be taken for the areas that are not spurted. With the application of intelligent spurting system, the aerial prevention techniques will be highly heightened.

4.2 Positioning and repositioning of damage point

In satellite remote sensing monitoring, DGPS should be utilized to accurately position the coordinates of control points so as to obtain the better rectification and registration of multi-temporal images. It can also be used to position the investigation point *in situ*. DGPS is also essential in airborne video monitoring. It is used to correct and join the images so that the damage point can be accurately positioned. Once the damage area has been detected by remote sensing, the navigating capacity of DGPS should be utilized to find the individual damaged trees so that measures can be taken accordingly.



Fig. 3.9 GPS application in hazard point recovery and investigation

State Administration of Forestry is now equipping GPS for all the monitoring stations in China. It can be sure that GPS technology will be widely used in the monitoring and prevention of forest insects and diseases.

5. Acknowledgments

The research described in this chapter was sponsored by National Forestry Administration, Anhui Province, Guangxi Province and Guangdong Zhuang Autonomous Region of the People's Republic of China. The work was carried out in the Chaohu region, Xuancheng region, Huangshan region of Anhui Province, Nanning region of Guangxi Zhuang Autonomous Region, Huiyang region of Guangdong Province. We wish to acknowledge the contribution of Wu Jian, Shi Jin, Xue Zhennan, Chen Murong, Tang Jian, Jiang Liya, Luo Jitong, Wang Fugui, Yang Xiuhao, Zhang Zhijian, Gao Shu, Zheng Wei, Chen Jiwen, Xie Cheng, Li Shiming, Ma Xiaoming, and others who worked during the course of GPS and its application.